

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Previously Presented) A charge pump capable of having multiple stages, comprising:

at least two pumping stages, each stage including:

an input terminal for accepting an input voltage,

an output terminal for delivering an output voltage, the output voltage different than the input voltage,

a first pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a first phase signal, and

a second pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a second phase signal, and

a first switch coupled between the input terminal and the output terminal and structured to disrupt a connection between the input and output terminals when activated by a switching signal;

a second switch coupled between the input terminal and the output terminal and structured to disrupt a connection between the input and output terminals when activated by a switching signal;

a third switch coupled between the first terminals of the respective first and second pumping capacitors and structured to disrupt a connection between the first terminals of the capacitors when activated by a switching signal; and

a pair of additional switches configured to separately couple the first and second pumping capacitors to the input and output lines such that for any pumping operation either one of the first and second pumping capacitors may selectively not be used;

the charge pump further including:

a switching network structured to couple the pumping stages either in a serial mode or a parallel mode depending on a state of the switching network.

2. (Previously Presented) The charge pump of claim 1 wherein there are at least four pumping stages, and the switching network comprises at least two switches.

3. (Previously Presented) The charge pump of claim 1 wherein some switches in the switching network and some of the switches in the pumping stages are structured to remain open during a charge pumping operation.

4. (Original) The charge pump of claim 1, further comprising:
a control circuit including an optimal stages finder coupled to the switching network.

5. (Original) The charge pump of claim 4, further comprising a phase assigner coupled to the optimal stages finder, and comprising a plurality of multiplexing circuits.

6. (Previously Presented) The charge pump of claim 5 wherein some of the switches in the switching network and in the pumping stages are structured to remain open during a charge pumping operation, and wherein the number in the plurality of multiplexing circuits is the same as the number of capacitors in the pumping stages plus the number of switches that do not remain open during the pumping operation.

7. (Previously Presented) The charge pump of claim 4 wherein the optimal stages finder comprises a comparison circuit structured to compare a reference voltage to a power supply voltage and generate an output signal.

8. (Original) The charge pump of claim 7 wherein the comparison circuit comprises:

- a first resistor ladder coupled to the power supply voltage;
- a second resistor ladder coupled to the reference voltage; and
- a set of comparators.

9. (Original) The charge pump of claim 8 wherein inputs of the comparators are coupled to the resistor ladders, and wherein outputs of the comparators are coupled to a signal latching circuit.

10. (Original) The charge pump of claim 9 wherein the signal latching circuit comprises:

- a first input and a second input;
- a first and a second latch; and
- a logic circuit coupled between the first and second input and structured to provide a signal to the first and second latch based on a signal on the first and second input.

11. (Original) The charge pump of claim 10 wherein the logic circuit comprises an OR gate having a first input terminal coupled to the first input of the signal latching circuit, a second input terminal coupled to an inverted signal of the second input of the signal latching circuit, and having an output terminal coupled to the second latch.

12. (Previously Presented) A variable stage charge pump, comprising:
a plurality of units, each unit including:
an input terminal and an output terminal;
a first switch coupled between the input terminal and a first terminal of a first capacitor, a second terminal of the first capacitor for receiving a pumping signal;

a second switch coupled between the input terminal and a first terminal of a second capacitor, a second terminal of the second capacitor for receiving a second pumping signal;

a third switch coupled between the first terminals of the first and the second capacitors;

a fourth switch coupled between the first terminal of the first capacitor and the output terminal; and

a fifth switch coupled between the first terminal of the second capacitor and the output terminal;

a plurality of phase selecting switches coupled to one of the capacitors in one of the units and structured to be coupled to one of the capacitors in another unit.

13. (Original) The charge pump of claim 12 wherein there are two units, and the phase selecting switch is coupled between the first terminal of the first capacitor of the first unit, and the first terminal of the first capacitor of the second unit.

14. (Original) The charge pump of claim 12 wherein the number of phase selecting switches in the second plurality is one less than the number of units in the plurality of units.

15. (Original) The charge pump of claim 14 wherein there are a first, second and third units and a first and second phase selecting switches, and wherein the first phase selecting switch is coupled between the first terminal of the first capacitor of the first unit and the first terminal of the first capacitor of the second unit, and the second phase selecting switch is coupled between the first terminal of the second capacitor of the second unit and the first terminal of the second capacitor of the third unit.

16. (Original) The charge pump of claim 12, further comprising:
a control circuit including an optimal stages finder coupled to the switching network.

17. (Original) The charge pump of claim 16, further comprising a phase assigner coupled to the optimal stages finder and comprising a plurality of multiplexing circuits.

18. (Previously Presented) A charge pump capable of having multiple stages, comprising:

at least two pumping stages, each stage including:

an input terminal for accepting an input voltage,

an output terminal for delivering an output voltage, the output voltage different than the input voltage,

a pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a phase signal, and

a switched diode coupled between the input terminal and the output terminal and structured to disrupt a connection between the terminals when activated by a switching signal;

the charge pump further including:

a switching network coupled between the pumping stages and structured to couple the pumping lines either in a serial mode or a parallel mode depending on a state of the switching network, the switching network comprising:

a first transistor coupled between the pumping stages;

a second and a third transistor coupled between one of the pumping stages and a first terminal of an auxiliary capacitor; and

a fourth transistor coupled between the first terminal of the auxiliary capacitor and a reference voltage.

19. (Canceled)

20. (Previously Presented) The charge pump of claim 18 wherein a control terminal of the second transistor is coupled to a signal that indicates the at least two lines of the charge pump should operate in a serial manner.

21. (Previously Presented) The charge pump of claim 18 wherein a control terminal of the fourth transistor is coupled to a signal that indicates the at least two lines of the charge pump should operate in a parallel manner.

22. (Previously Presented) The charge pump of claim 18 wherein a second terminal of the fourth transistor is structured to receive a phased signal.

23. (Original) The charge pump of claim 18, further comprising an output switched diode coupled to the output terminal.

24. (Previously Presented) The charge pump of claim 23 wherein the switched diode comprises:

an input terminal and an output terminal;

a first transistor coupled between the input terminal and output terminal;

a second transistor coupled between the input terminal and a first node and a first capacitor;

a third transistor coupled between the input terminal and a first node of a second capacitor;

a fourth transistor coupled between a control gate of the first transistor and a reference voltage; and

a fifth transistor coupled between the first node of the second transistor and the reference voltage.

25. (Original) The charge pump of claim 24 wherein the control gate of the fourth transistor and the control gate of the fifth transistor are coupled and driven with a signal that disconnects the output switched diode from the output terminal of the charge pump.

26. (Currently Amended) A method of connecting a set of pumping stages that include charge capacitors utilizing a plurality of switches forming a switching network, the method comprising:

accepting a voltage input signal at an input terminal;

applying a series of phase signals to the charge capacitors and applying phase signals to the switching network to separately couple any one of the charge capacitors to the input terminal and an output terminal such that for any pumping operation any combination of the charge capacitors may selectively not be used to produce an output voltage at the output terminal, the output voltage different than the input voltage; and

applying signals to the switching network coupled to the pumping stages, the signals for controlling whether the pumping stages should operate in a parallel or serial fashion.

27. (Previously Presented) The method of claim 26 wherein applying signals to the switching network comprises:

applying a signal to a switch coupled between two individual charge capacitors.

28. (Previously Presented) The method of claim 26 wherein applying signals to the switching network comprises:

applying a first signal to a first switch coupled between a first and a second charge capacitor; and

applying a second signal to a second switch coupled between the second charge capacitor and a third charge capacitor.

29. (Previously Presented) The method of claim 26 wherein applying signals to the switching network comprises:

applying a first signal to a first transistor to cause the charge capacitors to be coupled in a serial fashion, and applying a second signal to a second transistor in the switching network to cause the charge capacitors to be coupled in a parallel fashion.

30. (Previously Presented) The method of claim 26 wherein applying signals to the switching network comprises:

connecting the output signal from one charge capacitor to the input signal of another charge capacitor.

31. (Previously Presented) The charge pump according to claim 1 wherein the first and second phase signals are identical to each other.

32. (Previously Presented) The charge pump according to claim 1 wherein the first and second phase signals are in opposite phase from each other.

33. (Previously Presented) The charge pump according to claim 1 wherein the relationship between the first phase signal and the second phase signal is controllable by software code to achieve a desired output response from the charge pump.

34. (Previously Presented) A charge pump capable of having multiple stages, comprising:

at least two pumping lines, each line including:

an input terminal for accepting an input voltage,

an output terminal for delivering an output voltage, the output voltage different than the input voltage,

a pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a phase signal, and

a switch coupled between the input terminal and the output terminal and structured to disrupt a connection between the terminals when activated by a switching signal;

the charge pump further comprising:

a switching network structured to couple the pumping lines either in a serial mode or a parallel mode depending on the state of the switching network;

a control circuit including an optimal stages finder coupled to the switching network; and

a phase assigner coupled to the optimal stages finder, and comprising a plurality of multiplexing circuits structured to provide configurable phases to adjacent pumping capacitors.

35. (Previously Presented) A charge pump capable of having multiple stages, comprising:

at least two pumping lines, each line including:

an input terminal for accepting an input voltage,

an output terminal for delivering an output voltage, the output voltage different than the input voltage,

a pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a phase signal, and

a switched diode coupled between the input terminal and the output terminal and structured to disrupt a connection between the terminals when activated by a switching signal, the switched diode comprising:

an input terminal and an output terminal;

a first transistor coupled between the input terminal and output terminal;

a second transistor coupled between the input terminal and a first node and a first capacitor;

a third transistor coupled between the input terminal and a first node of a second capacitor;

a fourth transistor coupled between a control gate of the first transistor and a reference voltage; and

a fifth transistor coupled between the first node of the second transistor and the reference voltage;

the charge pump further including:

a switching network coupled between the pumping lines and structured to couple the pumping lines either in a serial mode or a parallel mode depending on a state of the switching network.

36. (Previously Presented) A charge pump capable of having multiple stages, comprising:

at least two pumping lines, each line including:

an input terminal for accepting an input voltage,

an output terminal for delivering an output voltage, the output voltage different than the input voltage,

a first pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a first phase signal, and

a second pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a second phase signal, the first and second phase signals being identical to each other, and

a first switch coupled between the input terminal and the output terminal and structured to disrupt a connection between the input and output terminals when activated by a switching signal;

a second switch coupled between the input terminal and the output terminal and structured to disrupt a connection between the input and output terminals when activated by a switching signal;

a third switch coupled between the first terminals of the respective first and second pumping capacitors and structured to disrupt a connection between the first terminals of the capacitors when activated by a switching signal;

the charge pump further including:

a switching network structured to couple the pumping lines either in a serial mode or a parallel mode depending on a state of the switching network.

37. (Previously Presented) A charge pump capable of having multiple stages, comprising:

at least two pumping lines, each line including:

an input terminal for accepting an input voltage,

an output terminal for delivering an output voltage, the output voltage different than the input voltage,

a first pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a first phase signal, and

a second pumping capacitor having a first terminal coupled between the input and output terminals and having a second terminal structured to accept a second phase signal, wherein the relationship between the first phase signal and the second phase signal is controllable by software code to achieve a desired output response from the charge pump, and

a first switch coupled between the input terminal and the output terminal and structured to disrupt a connection between the input and output terminals when activated by a switching signal;

a second switch coupled between the input terminal and the output terminal and structured to disrupt a connection between the input and output terminals when activated by a switching signal;

a third switch coupled between the first terminals of the respective first and second pumping capacitors and structured to disrupt a connection between the first terminals of the capacitors when activated by a switching signal;

the charge pump further including:

a switching network structured to couple the pumping lines either in a serial mode or a parallel mode depending on a state of the switching network.

38. (Currently Amended) A charge pump, comprising:
at least two pumping stages, each pumping stage comprising at least two charge
capacitors; and

a switching network configured to separately couple and uncouple the at least two
charge capacitors to input and output lines such that for any pumping operation, any combination
of the at least two charge capacitors may not be used, and the switching network further
configured to couple the at least two pumping stages in a serial or parallel arrangement.

39. (Previously Presented) The charge pump of claim 38, wherein the
switching network comprises at least five switches.

40. (Currently Amended) A circuit, comprising:
at least two pumping lines formed of at least two capacitors each; and
a plurality of switches configured to couple and uncouple each of the at least two
capacitors individually to input and output lines to provide configurable phases between each of
the at least two capacitors, and the plurality of switches further configured to configure the at
least two pumping lines in serial or parallel arrangements.